

**Ⓧ** **⚠** THIRD CT "C" REQUIRED IF LINE TO NEUTRAL LOADS ARE PRESENT

Note: For parallel unit installation CTs must be installed on the load side of the DPM power connection point.

**Danger!**  
Secondary leads of CT's (current sensors) must be properly terminated on P1 of the CT Interface Board (with a tightening torque of 4 in.lb) BEFORE the circuit being measured by the CT's is energized. Failure to do so may result in LETHAL VOLTAGE and severe damage to the CT's.


**IMPORTANT!**  
INSTALL CURRENT SENSORS WITH THE ARROWS, AND THE A,B,(C) MARKINGS ON EACH SENSOR AS SHOWN ABOVE. INSTALLATION ON PROPER PHASE AND IN CORRECT DIRECTION IS CRITICAL. BLACK WIRE ON MESTA SUPPLIED (FLEX-CORE) CT'S IS POSITIVE(+)

FACTORY INSTALLED JUMPERS ON P2 MUST REMAIN IN PLACE FOR SINGLE SYSTEM INSTALLATION

NEAREST BUILDING STRUCTURAL STEEL TO COMPLY WITH LOCAL AND NATIONAL ELECTRICAL CODES

BRANCH CIRCUIT PROTECTION DEVICE SUPPLIED BY CUSTOMER. SEE NOTES 1 & 2

STATUS RELAY CONNECTIONS  
0.5amps @ 125 VAC or  
1.0 amps @ 24 VDC



ETHERNET COMMUNICATIONS  
RS232 SERIAL COMMUNICATIONS

45400076.00  
CUSTOMER INTERFACE BD.

ENCLOSURE FRONT VIEW

**INSTALLATION NOTES:**

- Carefully read the installation section of the owner's manual prior to installing this equipment
  - Mesta DPM is a parallel installed device. Input connections specified are the only power connections to be made.
  - Branch Circuit Protection Device Current Rating: 125 Amperes. (Supplied by Customer)
  - Input Wiring Current Rating: 125 Amperes.
- Input wiring size should be selected according to the current rating indicated above and in accordance with the applicable national and local electric codes.
- 100 amp DPM Disconnect Switch: one conductor per pole

REVISIONS	Ⓧ Rev. 'D' REQUIRED IF LINE TO NEUTRAL LOADS ARE PRESENT (06/07/06)	MESTA ELECTRONICS, INC. 45900011E-1
	Ⓧ Rev. 'C' PC-BOARD 45400073 POLARITY CHANGE (08/28/07)	
	Ⓧ Rev. 'B' PC-BOARD 45400050 CHANGES TO 45400073. (01/23/07)	
	Ⓧ Rev. 'A' CURRENT SENSOR 'C' MADE OPTIONAL (11/08/06)	
Ⓧ Rev. 'E' PC-BOARD 45400076 NEW Interface/control panel(08/19/09)		

<small>THIS DRAWING AND ALL INFORMATION CONTAINED HEREIN IS THE PROPERTY OF MESTA ELECTRONICS, INC. AND IS NOT TO BE REPRODUCED, COPIED, OR TRANSMITTED IN ANY FORM OR BY ANY MEANS, ELECTRONIC OR MECHANICAL, INCLUDING PHOTOCOPYING, RECORDING, OR BY ANY INFORMATION STORAGE AND RETRIEVAL SYSTEM, WITHOUT THE WRITTEN PERMISSION OF MESTA ELECTRONICS, INC. FOR THE COPIER/OWNER OF THIS DRAWING AND SHALL BE RETURNED TO THE SOURCE AND SHALL BE DESTROYED UPON REQUEST. OTHER MARKS REGISTERED AS TRADE MARKS</small>	<small>WIRING CONNECTIONS SPECIFIED: ALL UNLESS NOTED BY SYMBOLS INTERCONNECT TERMINAL PINS: AS PER 15448-1004 TOLERANCES: XX .25/A XXX .25/A ANALOG .25/A THIRD ANGLE PROJECTION</small>	SCALE: N.T.S. DATE: 08/19/09 DPN: CAA/DLL DESIGNED: DJL/PL CHECKED: STD APPROVED: STD	TITLE: 100 AMP DPM CUST. INSTALLATION DIAGRAM DPN NO: 45900011 REV: E CDD FILE: 45900011E-1 SHEET NO: 1 OF: 1
---	---	--	--